

## RT42 Hand transmitter

The RT42 hand transmitter is a wireless transmitter which transmits the secwave code at the push of a button, and activates the secwave wireless receiver according to the selected mode.

The transmitter has a battery control function which checks the battery capacity. If the battery capacity is low, the LED flashes after the transmitter button is released.



RT42S5004A01-21K

### Technical specifications

|                       |  |
|-----------------------|--|
| Coding                | factory coding with secwave telegram, AES 128-bit encryption<br>Not compatible with Easywave products! |
| Frequency             | 868.30MHz  |
| Channels              | 4  |
| Range                 | typically 150 m in good free-field conditions  |
| Power supply          | 1x 3V battery, CR2032  |
| Operating indicator   | LED  |
| Operating modes       | 4x PULSE   |
| Operation             | transmission starts as soon as button is pressed   |
| Operating temperature | -20 °C to +60 °C   |
| Dimensions (W/L/H)    | 37/61.5/10.7 mm  |
| Weight                | 30g (including battery)  |
| Color                 | black similar RAL 9005   |

### Scope of delivery

- Hand transmitter including battery
- Key protection
- Operating manual

### Accessories (optional)

|                 |  |
|-----------------|--|
| RT42-ACC-01-21U | key protection for RT42/RT43<br>black similar to RAL9005 |
|-----------------|--|



### Models

| Product numbers  | Description   |
|------------------|---|
| RT42S5004A01-21K | Hand transmitter, secwave, 4x PULSE, metal bracket, black |