

RCP14 Plug-in socket dimmer

The RCP14 plug-in socket dimmer can be used to control and dim lighting of up to 250 W.

It can be operated using Easywave radio transmitters with a 1-button operation or 2-button operation or by using the dimmer switch directly.

Ohmic, capacitive and inductive loads can be dimmed. This also includes dimmable energy saving lamps (ESL) and dimmable LEDs.




RCP14E5001-01-01K

RECEIVERS

Technical specifications

Coding	Easywave Up to 32 transmitters can be programmed.
Frequency	868.30 MHz
Channels	1
Power supply	230 V AC, 50 Hz
Power consumption	0.7 W standby
Operating modes	dim with memory (2- and 1-button operation) dim without memory (2- and 1-button operation) control fixed brightness levels (2- and 1-button operation)
Output	electronic switch
Maximum contact load	
- ohmic load	250 W
- inductive load	20 - 250 VA
- LED + ESL	7 - 100 VA
- capacitive load	250 VA
Operating temperature	-20 °C to +35 °C
Dimensions	50 x 120 x 75 mm
Color	white similar to RAL 9003

Plug system



Scope of delivery

- Plug-in socket dimmer
- Operating manual

Models

Product numbers	Description	Plug system
RCP14E5001-01-01K	Plug-in socket dimmer 1-channel, white	D/A/NL/S/N