

RT30 Hand transmitter

The RT30 hand transmitter is designed for universal use. It can be used together with any Easywave receiver and in any of the operating modes available.

It may be used to control roller shutters for example or, more generally, to switch electrical devices on or off.

An easily visible LED lights up when the battery needs to be changed.




RT30E5004-01-02K

RT30E5001-01-22K


Technical specifications

Coding	factory coding with Easywave telegram
Frequency	868.30 MHz
Channels	1 or 4
Range	typically 150 m in good free-field conditions
Power supply	1x 3V battery, CR2032
Operating indicator	LED
Operation	transmission lasts as long as the button is pressed (maximum 36 seconds)
Function	depends on the receiver (see models)
Operating temperature	-20 °C to +60 °C
Dimensions	38 x 60 x 14 mm (without wall holder)
Weight	25 g (including battery)
Color	glossy white similar to RAL 9003 glossy black similar to RAL 9005

Models



RT30E5001-01-xxK
1x UP/STOP/DOWN



RT30E5004-01-xxK
4x PULSE

Scope of delivery

- Hand transmitter including battery
- Wall holder
- Mounting material
- Operating manual

Accessories (optional)

RT30-ACC-01-02P	Key ring, transparent
RT30-ACC-03-02P	Wall holder, glossy white
RT30-ACC-03-22P	Wall holder, glossy black



RT30-ACC-01-02P



RT30-ACC-03-02P



RT30-ACC-03-22P

Models

Product numbers	Description	Function
RT30E5001-01-02K	Hand transmitter 1-channel, glossy white	1x UP/STOP/DOWN
RT30E5001-01-22K	Hand transmitter 1-channel, glossy black	1x UP/STOP/DOWN
RT30E5004-01-02K	Hand transmitter 4-channel, glossy white	4x PULSE
RT30E5004-01-22K	Hand transmitter 4-channel, glossy black	4x PULSE